

Replacing LCD Panel for CR630/CR1200

1-1 Replacing the LCD Panel



- ◆ Go to the screen on the cutter and peel off the black cover.

1-2 Replacing the LCD Panel



- ◆ Place a screwdriver into a screw in this area.
- ◆ Place a pair of pliers to the bolt on the underneath side.
- ◆ Remove each screw one at a time.
- ◆ When complete, the screen, buttons, and control panel will be removed.



1-3 Replacing the LCD Panel

- ◆ Place the new parts in place of the old ones.
- ◆ Reapply screws and bolts tightly.
- ◆ Remove the right side end cap by removing each of 4 black screws on the right side plate.
- ◆ There are 2 screws in the front of the cutter, and 2 in the back.
- ◆ Once complete, lay the cutter on its back.
- ◆ Unscrew each of the 8-10 screws on the bottom plate.
- ◆ (It is recommended an electric screwdriver be used for this task. These screws are extremely tight)

1-4 Replacing the LCD Panel

- ◆ Once the bottom plate is loose, lay it down to see the insides.
- ◆ The motherboard for the machine is on the right hand side.
- ◆ Once there, follow the cables for the previously removed screen items to their place on the motherboard.
- ◆ Remove each cable from its place on the motherboard one at a time, replacing it with the new one as you go.
- ◆ Once the new cables are plugged in, place the bottom plate back in place on the bottom of the cutter and bring the cutter back up to its normal sitting position.
- ◆ (Do not reattach screws on the base plate yet)

1-5 Replacing the LCD Panel

- ◆ Plug in the cutter and turn it on.
- ◆ Test the functionality of the control panel and screen and make sure everything is working.
- ◆ Once testing is complete, reattach all base plate screws.
- ◆ Place screen cover on the LCD screen.
- ◆ Replacement is now complete!

The End

Please review our tutorials for more information on particular features.

<http://www.cutterpros.com/downloads> for further information.

To speak with a technician, submit a ticket at <http://www.cutterpros.com/support/> or call 888-828-8776 x227

CutterPros.com/Hahn Ventures LLC is NOT liable for any software/attachments/instructions/download links/content contained in this presentation. Use the contents of this presentation AT YOUR OWN RISK. CutterPros.com/Hahn Ventures LLC is NOT responsible for any damages incurred to your computer hardware/software or any possible viruses/Trojans/malware or any other type of damaging programs that may be contained in the links and/or attachments. It is your responsibility to verify the contents before using any of the information contained in this presentation. By using the contents in this email you agree to hold CutterPros.com/Hahn Ventures LLC harmless of all liability and damages. You agree that you are totally responsible for what you put on your computer, software you install on your computer and files you download to your computer.

CUTTERPROS.COM